

INTUSONIC PAA71 Mixer di linea per microfono

Mixer linea microfono, 7 canali

Art.n.: 12604176

GTIN: 5060502923219



Prezzo di listino: su richiesta €

incl. 19% IVA

Descrizione :

The INTUWORX PAA71 is 7-channel mic/line mixer and the perfect center of any installed sound system. It offers 5 multi-purpose inputs which can either be fed with a balanced microphone signal or an unbalanced stereo line signal. One further balanced stereo line level input is specifically useful for sources at larger distance, like a mixer on a stage, or the output of a secondary room's system. The same input can be switched to receive its input signal from the 3.5mm TRS jack on the front, or the built-in LINKOUSTIC 4.2 wireless audio link. An additional dedicated microphone input with adjustable talkover (priority) provides control over announcements. Every input -- with the exception of the balanced stereo input -- is equipped with rear-panel gain control and a front-panel 2-band equalizer. The external shutdown and emergency signal input connections allow integration with central announcement and evacuation systems where required.

Features :

- Montaggio su rack (19") 48,3 cm
 - Per maggiori informazioni su questo prodotto, consultare "Download" nella scheda tecnica
- Dotazione della fornitura**
- 1 x Manuale d'uso, 1 x mixer, 1 x Cavo di rete/Cavo di alimentazione, 10 x morsetto a vite, 1 x connettore, 4 x piede, 1 x Antenna

Dati tecnici :

Alimentazione elettrica: 115/230 V AC, 50/60 Hz

Potenza totale installata: Massimo 12 W

Logistica

EAN / GTIN: 5060502923219

Peso : 3,25 kg

Lunghezza : 0.54 m

Larghezza : 0.33 m

Altezza : 0.10 m

Classe di protezione:	CL I
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite Dispositivi a freddo (M) cavo di alimentazione con spina di protezione (in dotazione)
Fusibile di protezione del dispositivo:	5 x 20 mm, T 0,5 A fusibile sostituibile
Intervallo di frequenza:	20 - 20000 Hz
Rapporto segnale-rumore:	>82 dB line
Distorsione armonica totale:	<0,05 % a 1 kHz
Tensione virtuale:	12 V DC
Colore della custodia:	Nero
LED di stato:	Power, Pairing, Indicatore di livello
Collegamenti:	Ingresso: 1 x Jack da 6,3 mm (sim.)
Canali:	Canale di ingresso: 5 x Stereo with interruttore Mic-Line via RCA, channel control via manopola, regolatore a 2 bande EQ
Equalizzatore:	1 x regolatore a 2 bande Mono
Struttura della custodia:	Montaggio su rack (19") 48,3 cm
Misure:	Larghezza: 48,3 cm Profondità: 19 cm Altezza: 4,4 cm
Peso:	2,70 kg